



ENTERTAINMENT

BOOMER 6 is a COB LED RGBW Zoom PAR with an effect RGB ring front face. It's small in size, powerful and versatile in dynamic effects. It is powered by a 60 Watts RGBW COB LED and features a fast zoom of 5° to 45°. The front ring is pixel control with the built-in macros making this compact zoom PAR ideal for small venues, clubs, theatre and indoor events.

SOURCE : Light source: 1 x 60 Watts RGBW COB LED
LED Ring: 24 x 0.5 Watts RGB LEDs
LED life expectancy: 50,000 Hrs.

OPTICAL SYSTEM : Beam angle: 5° to 45°
High Efficiency Lens

DYNAMIC EFFECTS : High Speed Zoom
Color mixing: RGBW
Electronic variable strobe
Built-in dynamic macros

CONTROL & PROGRAMMING : Control protocols: DMX
Display: LCD screen display
Control channels: 13, 18 CHs

ELECTRICAL : Input voltage: 110-240V/50-60Hz
Power consumption: 80 watts

CONNECTIONS : DMX connections: 3 pin Cable In/Out male and female
Power connections: Power Cable In/Out male and female

PHYSICAL : Dimensions: 260 x 200 x 160mm
Net weight: 2.8 Kg
Color: Black
IP rating: 20